



Electrical Safety

Extension Cords

Extension Cords Are Everywhere

Extension cords can be found in nearly all vocational settings due to the widespread use of electronic equipment and electrically powered tools. They are more susceptible to damage than fixed wiring because they are exposed, flexible and unsecured. The normal wear and tear on extension cords can loosen or expose internal wires and create hazardous conditions.

Extension cords are intended for temporary use only and are not intended to replace fixed wiring. Three-prong wire cords that have not been extensively used and that are not modified represent less of a risk of electric shock.

Cord Damage

- Extension cords can be damaged by doors, window edges, staples, fasteners, abrasion from adjacent materials and simple aging.
- If the electrical conductors become exposed, there is a high risk of injury due to electric shock and fire.

Strain Relief

- The flexible cord material must connect to devices in ways that prevent tension at joints and terminal screws.
- For flexibility, the cord material is made of finely stranded wires.
- Stressing a cord can cause the strands of one conductor to loosen from a terminal screw and touch other conductors.
- Intact "strain reliefs" help to keep cord termination points safe.

Durability

- Electrical codes [e.g., Article 400 of the National Electrical Code (NEC)] provide construction requirements based on location, use, amperage requirements and other factors.

These construction requirements are derived from the National Electrical Code and are required to be marked on the cord at approximately every foot. Examples of these code types are S, ST, SO, STO, SJ, SJO, SJT and SJTO. These ratings establish cable voltage ratings, indoor or outdoor use conditions, and cable jacket construction requirements described in Article 400 of the NEC.



Grounding

- ✔ Extension cords must be a three-prong type, which will provide grounding for the equipment being used.
- ✔ Never use an extension cord with a missing or damaged ground prong.

Wet Conditions

- ✔ When a cord connection is wet, electrical current can leak from a hot wire to the grounding conductor and to whoever handles that connection. Such leakage can occur not just on the face of the connector but on any wet portion.
- ✔ Limit the exposure of cords, connectors and tools to excessive moisture by using water-tight or sealable connections.
- ✔ The use of ground-fault circuit interrupters (GFCIs) greatly reduces the danger inherent in exposure to water and is advised for all applications.

Avoid Hazards

- ✔ Use factory-assembled cords that are properly rated for the application.
- ✔ Only use extension cords that are a three-prong type.
- ✔ Only use extension cords that are marked with a designation of heavy or extra-heavy usage.
- ✔ Only use cords, connection devices and fittings that are equipped with strain reliefs.
- ✔ Remove cords from receptacles by pulling on the plugs, not on the cords.
- ✔ Conduct regular cord inspections. Any damaged, unmarked or modified cords should be cut up and thrown away.
- ✔ Use GFCIs at all times.
- ✔ Only use extension cords for temporary applications. Long-term electrical use requires fixed wiring.

Inspection

- ✔ Inspect and test all cords before use.
- ✔ Do not use a damaged cord.
- ✔ Implement a test and ground assurance program for everyone's safety!

The material provided in this document is for general information purposes only. Nothing in this document should be construed as legal advice or the provision of professional consulting services. Reasonable care has been utilized to compile this information. However, no warranty or representation is made regarding the accuracy or completeness of the information. Distribution of this information does not constitute an assumption by us of your obligations to provide a safe workplace. We make no representation or warranty that our activities or recommendations will place you in compliance with law, relieve you of potential liability or ensure your premises or operations are safe. We exercise no control over your premises or operations and have no responsibility or authority to implement loss prevention practices or procedures. Maintaining a safe workplace in accordance with all laws is your responsibility.